

SONIFEX
Redbox

AUDIO INTERFACES

Redbox - Matching Converters

Audio Specification For RB-BL2

Maximum Input Level:	+28dBu
Maximum Output Level:	+28dBu
Input Impedance (RCA):	>10k unbalanced
Input Impedance (XLR):	>20k balanced bridging
Output Impedance (RCA):	<50
Output Impedance (XLR):	<50
Distortion:	0.01% THD @ 1kHz, ref +8dBu output
Noise:	-100dB, unity gain, ref +8dBu output
Common Mode Rejection:	>66dB typically
Frequency Response:	20Hz to 20kHz ± 0.1 dB (600 Ω load, ref 1kHz)
Gain Range:	Unbalanced Output : -28dBu to 0dBu, ref 0dBu into balanced XLR input Balanced Output : -15dBu to +15dBu, ref -15dBu into unbalanced RCA input

Connections

Inputs:	2 x RCA phono (Unbal), 2 x XLR 3 pin female (Bal)
Outputs:	2 x XLR 3 pin male (Bal), 2 x RCA phono (Unbal)
Mains Input:	Filtered IEC, switchable 110-120V, or 220-240V, fused, 6W max
Fuse Rating:	Anti-surge fuse 100mA 20 x 5mm (230VAC) Anti-surge fuse 250mA 20 x 5mm (115VAC)

Equipment Type

RB-BL2:	Single stereo bi-directional matching converter
---------	---

Physical Specification

Dimensions (Raw):	28cm (W) x 10.8cm (D) x 4.2cm (H) (1U) 11" (W) x 4.3" (D) x 1.7" (H) (1U)
Dimensions (Boxed):	36cm (W) x 20.5cm (D) x 6cm (H) 14.2" (W) x 8" (D) x 2.4" (H)
Weight:	Nett: 1.0kg Gross: 1.4kg Nett: 2.2lbs Gross: 3.1lbs

RB-BL2 Single Stereo Bi-Directional Matching Converter

The RB-BL2 is a bi-directional stereo unit for interfacing domestic or semi-pro unbalanced equipment to professional balanced line levels, and vice-versa.

The two XLR-3 electronically balanced inputs have an impedance of 20k Ω bridging and are routed to two unbalanced RCA (phono) outputs with an output impedance of <50 Ω .

The two RCA unbalanced inputs have an impedance of 20k Ω and are routed to two balanced XLR-3 outputs with an output

impedance of <50 Ω . All connections are on the rear panel.

The output gain can be adjusted for left and right channels by using pre-set potentiometers accessible through the rear panel.



// The output gain can be adjusted for left and right channels by using pre-set potentiometers accessible through the rear panel. //

SONIFEX

www.sonifex.co.uk

t:+44 (0)1933 650 700

f:+44 (0)1933 650 726

sales@sonifex.co.uk

61 Station Road
Irthlingborough
Northants NN9 5QE
United Kingdom

