

SONIFEX

www.sonifex.co.uk

t:+44 (0)1933 650 700

f:+44 (0)1933 650 726

sales@sonifex.co.uk

signal
LED

Signalled Preconfigurations

Please note that your Signalled sign has been preconfigured for the following operation, depending on the sign chosen





Please note that your SignalLED sign has been preconfigured for the following operation, depending on the sign chosen



SIGNALLED PRECONFIGURATIONS

| Top Level Part Number | Slave | Master (Side with connections) | No Input | Input 1 | Input 2 | Both Inputs |
|-----------------------|-----------------------|--------------------------------|--------------------|---|---|--|
| LD-20F1MCL | | MIC LIVE | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-20F1ONA | | ON AIR | Turns the sign off | Turns the whole sign solid green when connected to 0V | Turns the whole sign solid red when connected to 0V | Turns the sign off |
| LD-20F1REC | | RECORD | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1ADB | AD BREAK | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1DOR | DOOR | | Turns the sign off | Turns the whole sign solid blue when connected to 0V | Turns the whole sign solid red when connected to 0V | Turns the sign off |
| LD-40F1EXIT | EXIT | | Turns the sign off | Turns the whole sign solid green when connected to 0V | Turns the whole sign solid red when connected to 0V | Turns the sign off |
| LD-40F1INT | INTERVIEW IN PROGRESS | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1MCL | MIC LIVE | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1MET | MEETING IN PROGRESS | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1NOE | NO ENTRY | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1OBT | OBIT | | Turns the sign off | Turns the whole sign solid magenta when connected to 0V | Turns the whole sign solid white when connected to 0V | Turns the sign off |
| LD-40F1ONA | ON AIR | | Turns the sign off | Turns the whole sign solid green when connected to 0V | Turns the whole sign solid red when connected to 0V | Turns the sign off |
| LD-40F1PHN | PHONE | | Turns the sign off | Turns the whole sign solid yellow when connected to 0V | Turns the whole sign solid white when connected to 0V | Turns the sign off |
| LD-40F1REC | RECORD | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F1REH | REHEARSAL | | Turns the sign off | Turns the whole sign solid blue when connected to 0V | Turns the whole sign solid red when connected to 0V | Turns the sign off |
| LD-40F1SIL | SILENCE | | Turns the sign off | Turns the whole sign solid red when connected to 0V | Turns the whole sign solid orange when connected to 0V | Turns the sign off |
| LD-40F1TRF | TRAFFIC FLAG | | Turns the sign off | Turns the whole sign solid orange when connected to 0V | Turns the whole sign solid green when connected to 0V | Turns the sign off |
| LD-40F2ONA-MCL | ON AIR | MIC LIVE | Turns the sign off | Turns the MIC LIVE segment solid red when connected to 0V | Turns the ON AIR segment solid green when connected to 0V | Turns the MIC LIVE segment solid red and the ON AIR segment solid green when connected to 0V |
| LD-40F2ONA-SIL | ON AIR | SILENCE | Turns the sign off | Turns the SILENCE segment solid orange when connected to 0V | Turns the ON AIR segment solid red when connected to 0V | Turns the SILENCE segment solid orange and the ON AIR segment solid red when connected to 0V |
| LD-40F2TX-REH | TX | REH | Turns the sign off | Turns the REH segment solid blue when connected to 0V | Turns the TX segment solid red when connected to 0V | Alternates REH in solid blue, TX in solid red |



SIGNALLED PRECONFIGURATIONS